

EMERGENCY CONVERSION KIT 2.5W 20-90VDC 3HR WITH REMOTE LED INDICATOR AND MANUAL TEST BUTTON INTEGRAL

ILEMPK011



Note: Warranty increased to 5 years on 27/03/2025

Details

Barcode:	5055788288862
Quick Order Code:	165555
Category:	Emergency
Range Name:	Conversion Kit
Product Type:	Emergency Conversion Kit
Product Body Finish:	Matt white. End cap blue
Market Segment:	Commercial indoor
Finish:	Matt white. End cap blue
Warranty (Years):	5

Physical Data

Product Length (mm):	240
Product Depth (mm):	28
Product Width (mm):	50
Product Weight (g):	215
Material:	Polycarbonate
Construction:	Injection moulding
Bulb or Luminaire Shape:	Rectangle
Luminaire Fixing:	In Ceiling
Placement / Application:	Indoor, Emergency Lighting

Electrical Data

Power (W):	2.5
Power Consumption (W) :	2.5
Input Voltage (V):	220-240
Output Voltage (V):	20-90
Battery Configuration:	LiFePo4
Driver Included:	Yes
Electric Current:	AC

Light Data

Frequency Range (Hz): 50/60

Environment

CE RoHS: Yes
IK Rating (Impact Protection): IK04
IP Rating (Ingress Protection): IP20
Lowest Operating Temperature (°C): 5
Maximum Operating Temperature (°C): 45

Packaging

Barcode: 5055788288862
Package Weight (g): 250
Package Length (mm): 28
Package Width (mm): 240
Package Depth (mm): 50